

**Datasheet**
**Description**

Farran Technology offers the WGNS series of noise sources to be used in conjunction with the FBC down converters for use as frequency extenders for noise figure measurement test system. The WGNS-XX is a fullband noise source. The WGNS-08 covers the full F band 90-140 GHz.


**Features**

- Full waveguide band
- High ENR
- Uniform level of noise power spectral density
- Compatible with Agilent NFA
- Compatible with Agilent PXA with noise figure personality
- Convenient packing to match the VNA frequency extension

**Applications**

- Frequency extenders for noise figure measurement systems
- Communications
- OEM test instrumentation
- EW and ECM systems
- Radar front ends

Specification	Unit	Min	Typ	Max
System Operating Frequency	GHz	90		140
ENR	dB		12	
ENR Flatness	dB			+/-1.5
Trigger Voltage	V		+28	
Pause between triggering pulses	ms	0.5		
VSWR				1.4:1
Test Port Interface	-	WR-08 UG-387/U-M		
Trigger connector	-	BNC (F)		
Power Requirements	-	240/110 V AC		
Weight	kg		3.5	
Dimensions (L x W x H)	-	200 x 120 x 90		

**Datasheet**
